

## 5.17\_V2.0 SWITCH FROM BEP B TO BEP A

*Last Revised: May 26, 2016*

**Filename: switch\_bepb\_a**

### **BRIEF FUNCTIONAL DESCRIPTION:**

This is a contingency procedure to switch from using BEP B to using BEP A.

The sequence of actions will be:

1. Issue power-down command for FEPs and video boards
2. Select BEP A
3. Cold boot BEPs
4. Verify BEP A boots from SW TLM
5. Check HW LEDs
6. Check SW LEDs
7. Issue power-down command for FEPs and video boards

The procedure does a cold boot to get the instrument into a known state, so if there were patches loaded into BEP A they will be lost. The operator should be cognizant if patches must be subsequently loaded. The final power-down command ensures that the control register in the newly active BEP reflects the current FEP power status.

### **ASSUMED INSTRUMENT STATE:**

Assumes that DPA A & B are on.

Assumes BEP B is functional and can accept a power-down command.

### **SPECIAL INITIAL CONDITIONS:**

None.

### **OPERATIONAL CONSTRAINTS/CAUTIONS:**

Any patches loaded into BEP A will be removed as a result of this procedure. This procedure resets the focal plane temperature setting.

### **REFERENCES:**

### **CHANGE HISTORY:**

#### **V1.0**

- Initial version, based on switch\_bepa\_b V2.1
- Added warnings about focal plane temperature setting.
- Minor formatting change to table.
- Added steps to power down FEPs and video boards before and after the switch.
- Added initial state for BEP B.

## V2.0

- ACIS team signed-off version.

This page is intentionally blank

Table 1: SWITCH FROM BEP B TO BEP A(Page 1)

Step #	Title (Revision 5.17_V2.0 )	Time Req (m)	Command Description	Command Mnemonic	Telemetry Description	Telemetry Mnemonic	Expected Value
1	<b>Issue Power Command</b>						
1.1	Power off FEPs & Video Boards	1	changeConfigSetting	WSPOW00000			
2	<b>Select BEP A</b>						
2.1	Select BEP A	1		1BSELICL(0)			
3	<b>Cold Boot BEPs</b>						
3.1	Set boot modifier off	1	DPA Boot Modifier	1BMODIBM(0)			
3.2	Set warm boot flag off	1	DPA Cold Boot	1WRMBTBSB(0)			
3.3	Halt BEP	1	DPA Command Reset	1RSETIRT(1)			
3.4	Restart BEP	1		1RSETIRT(0)			
3.5	Check BEP A Boot	2					
3.6	Check HW LEDs	2			BEP Select BEP FIFO Not Full BEP FIFO Not Empty	1STAT4ST 1STAT6ST 1STAT7ST	0 1 0
3.7	Check SW LEDs	2			BEP initialization Watchdog boot Science run status	1STAT3ST 1STAT2ST 1STAT1ST 1STAT0ST	0 1 1 0or1

Table 1: SWITCH FROM BEP B TO BEP A(Page 1)

Step #	Units	Telemetry EGSE	Other Verifier	Crit	Description	Notes	RT Con	Tlm Fmt	Min Alt	SIM Pos
1										
1.1		Verify cmdResult==1 commandEcho 773		1 1			Y	1or2		
2										
2.1					1BSELICL=0 selects BEP A		Y	1or2		
3										
3.1					Disable uplink boot		Y	1or2		
3.2					Cold boot active BEP		Y	1or2		
3.3					Hold active BEP reset line		Y	1or2		
3.4					Release BEP reset line		Y	1or2		
3.5		Check bepStartupMessage: bepTickCount < 10; version=11; warmBootFlag = 0; patchValidFlag = 1 Check swHousekeeping messages: startingBepTickCount < 10; endingBepTickCount= startingBepTickCount+640; version = 11		1 1 1 1 2 2 1			Y	1or2		
3.6				2 2 2	0 indicates BEP A is selected 1 means FIFO not full 0 means FIFO empty		Y	1or2		
3.7				1 2 2 2	0 means BEP SW is running 1 means no watchdog boot 1 means science idle This bit toggles to indicate BEP is running		Y	1or2		

Table 1: SWITCH FROM BEP B TO BEP A(Page 2)

Step #	Title (Revision 5.17_V2.0 )	Time Req (m)	Command Description	Command Mnemonic	Telemetry Description	Telemetry Mnemonic	Expected Value
4	<b>Issue Power Command</b>						
4.1	Power off FEPs & Video Boards	1	changeConfigSetting	WSPOW00000			
	Total Time:	13					

Table 1: SWITCH FROM BEP B TO BEP A(Page 2)

Step #	Units	Telemetry EGSE	Other Verifier	Crit	Description	Notes	RT Con	Tlm Fmt	Min Alt	SIM Pos
4										
4.1		Verify cmdResult==1 commandEcho 773		1 1			Y	lor2		