

4.29_V1.0 TURN OFF DEA B (realtime version)

Last Revised: July 21, 2015

Filename: deab_off

BRIEF FUNCTIONAL DESCRIPTION:

This is an “atomic” procedure which simply turns off the DEA side B. The instrument must not be in bakeout mode when this procedure is executed. The video boards should be powered off during this procedure. The “Enable” and “On” verifiers will only be valid if one side of the DPA is on.

The sequence of actions will be:

1. turn off and disable DEA power supply side B

ASSUMED INSTRUMENT STATE:

Assumes that the PSMC has power from the spacecraft.

The instrument **MUST NOT** be in bakeout mode.

The video boards should be powered down before executing this procedure.

SPECIAL INITIAL CONDITIONS:

OPERATIONAL CONSTRAINTS/CAUTIONS:

REFERENCES:

CHANGE HISTORY:

none

Table 1: TURN OFF DEA B (realtime version)(Page 1)

Step #	Title (Revision 4.29_V1.0)	Time (mins)	Command Description	Command Mnemonic	Cmd EGSE	Seq Key	Telemetry Description	Telemetry Mnemonic
1	Turn off DEA B							
1.1	DEA Power B Off	1	DEA PS Off B	1DEPSBOF				1DEPSB
1.2	Disable DEA PS B	1	DEA PS B Dis	1DEPSBDS			DEA B Dis DEA +24 V B DEA Input V B DEA Input I B DEA +6 V B DEA -6 V B DEA +15 V B DEA -15 V B DEA +28 V B	1DEPSBX 1DEP2BVO 1DE28BVO 1DEICBCU 1DEP0BVO 1DEN0BVO 1DEP1BVO 1DEN1BVO 1DEP3BVO
	Total Time	2						

Table 1: TURN OFF DEA B (realtime version)(Page 1)

Step #	Expected Value	Units	Telemetry EGSE	Other Verifier	Crit	Description	Notes	RT Con	Tlm Fmt	Min Alt	SIM Pos
1											
1.1	OFF					Ignore if DPA unpowered			1,2,4,6		
1.2	DIS 0 25.0-34.0 0 0 0 0 0 0	V V A V V V V V			1 2 2 2 2 2 2	Ignore if DPA unpowered Expect DEA side B power at 0.0 W			1,2,4,6		

This page is intentionally blank